
FORM NO 51.61 Apr Approved For Release 2002/01/18: CLARDF8300415R009200060008-5
CLASSIFICATION SECRET/CONTROL - U.S. OFFICIALS ONLY 25X1A CENTRAL INTELLIGENCE AGENCY REPORT NO. INFORMATION REPORT CD NO. 3/7/ COUNTRY Germany (Russian Zone) DATE DISTR. **\$** October 1951 SUBJECT Berlin-Type Section Blocking System NO. OF PAGES ļ 25X1A PLACE ACQUIRED NO. OF ENCLS. (LISTED BELOW) 2- (Schematic DOCUMENT HAS AN ENGLOSURE ATTACHED diagram; DETACH explanatory not DATE OF I SUPPLEMENT TO REPORT NO. in German and ACQUIRED English) 25X1X **ILLEGIB** SOURCE A schematic diagram representing the conversion of the double-track section blocking system to single-track operations as applied in the Berlin railroad district with pertinent explanatory notes was obtained at the Directorate General, Railroads, Berlin. The diagram of a modified section blocking system was copied from an original blueprint. For explanatory notes, see Annex 2. The lines in the Berlin railroad district provided with Berlin-type section blocking facilities were reported previously. 2. The attached reports are forwarded to you on loan. 25X1A SECURITY INFORMATION 25X1A CLASSIFICATION SECRET/CONTROL - U.S. OFFICIALS ONLY



Approved For Release 25 10 FT 18 CONTROP 83-003 15 1009 200 U.S. OFFICIALS ONLY

Legend to Annex 2

Explanatory Notes on the Berlin-Type Section Blocking (Translation)

- 1. The closing or interruption of the circuit is indicated by the following symbols: indicating a closed circuit, standing for an interrupted circuit. In addition to the standard four-field system the red-boxed units and the units underlined in red are required for the Berlin-type section blocking system. The starting field is simultaneously used as co-operating field. On the attached schematic diagram starting field x is blocked, i.e. signal x is locked in stop position, while starting field U is clear and signal U is in clear position.
 - a. Gircuit arrangement while a train is moving toward signal U:

Track locking device U is applied, contact Ff is interrupted, magnetic switch 2 becomes dead and by interrupting contact 2 31/32 continues to prevent the supply of current. After the train has passed signal U, starting field U is blocked. Circuit connections: From J.W. via

- (1) A contact at the starting field (switched over)
- (2) Field coils, starting field U
- (3) Contact 11/12 (base position) to the neighboring Block Station II
- (4) Contact at end field (base position)
- (5) Field coils end field W
- (6) Contact at end field (base position)
- (7) Contact 51/52 (base position) to Block Station I
- (8) Contact 31/32 (base position)
- (9) Contact at starting field U (switched over) back to I. W.

SECRET CONTROL U.S. CEFICIALS ONLY

Approved For Release 2002/01/18 : CIA-RDP 83-004 15 8009

SECKET GONTROL U.S. OFFICIALS ONLY

Legend to Annex 2 of

b. Circuit arrangement for back blocking.

From I.V.

Block Station II via

- (1) Contact at end field W (switched over)
- (2). Contact for semaphore arm in base position
- (3) Contact at end field W switched over
- (h) Field coils end field W
- (5) Contact 61/62 (base position) to Block Station I
- (6) Contact at starting field U in base position
- (7) Field coils starting field U
- (8) Contact at starting field U (base position)
- (9) Contact 31/32 to Block Station II
- (10) Contact 51/52
- (11) Contact at end field W (switched over) to I.W.

The train after passing U releases the track-locking device. Contact Ff is closed again; starting field U is blocked and thus the plunger and locking bolt contact in the circuit of magnetic switch. 2 is closed again. Magnetic switch 2 is operated and after de-blocking starting field U the original position is restored.

c. Transmission of clear signal from I to II (from starting field U to starting field X):

By operating the lever for starting field U the early closing contact of starting field U in the circuit of magnetic switch l is closed. Magnetic switch l is activated thus causing the four contacts of magentic switch l in the section blocking circuit of Block Station I to be switched over when starting field U is blocked.

SECHET CORTROL U.S. OFFICIALS ONLY

Approved For Release 2002/01/18: CIA-RDP83-00415R009200060008-5

SECRET CONTROL U.S. OFFICIALS ONLY

Legend to Annex 2 of

d. Circuit arrangement:

From I.W. to Block Station I

- (1) Contact at starting field U switched over
- (2) Field coils starting field U
- (3) Contact 21/22 switched over
- (h) Contact 51 1 to block Station II (51/52 interrupted)
- (5) Contact at starting field X in base position
- (6) Field coils starting field X
- (7) Contact at starting field X in base position
- (8) Contact 11/12 1 (base position) to Block Station I
- (9) Connection 61 (61/62 interrupted)
- (10) Contact 41/42 1 switched over
- (11) Contact at starting field U switched over, back to I.W.

Now signal U is fixed in its base position by the blocked signal locking device, while signal X, by de-blocking of the starting field X (co-operating field), has become free. In the circuit of magnetic switch 2 at Block Station I the locking bolt contact of starting field is switched over and is thus closed. The contact of starting field X previously closed in the circuit of magnetic switch 2 of Block Station II is now interrupted ().

Explanation of abbreviations and sumbols:

I.W. - A.C. Inductor
I.W. - Outgoing current
I.W. - Return current

The German original of the explanatory notes is attached. For symbols, which were not transferred to translation, see original German text.

SECRET CONTROL U.S. OFFICIALS ONLY

Approved For Release 2002/01/18 CIA-RDP83-00415R0092000 U.S. OFFICIALS BALLS AN ENCLOSE

DO NOT DETACH

Streckenblock für eingleisigen Betrieb

Berliner Form

Die Schaltung ist nach dem Prinzip der "Pfeilschen Kurzschaltung" _ = Kontakt geschlossen = Stromdurchfluss -= Kontakt geöffnet = kein Stromdurchfluss. Zusätzlich zur normalen "4 Felder" Form sind die rot umrahmten und rot nachgezeichneten Teile erforderlich. Das Anfangsfeld gilt gleichzeitig als Erlaubnisfeld - die mechanische und die elektrische Tastensperre ist unwirksam gemacht. Im vorliegenden Fall ist Anfangsfeld x geblockt, also Signal x durch den Signalverschluss in der Haltlage verschlossen. Anfangsfeld U ist entblockt, also Signal U frei.

Zugfahrt auf Signal U:

Fahrstrassenfestlegung "u" wird geblockt - Kontakt Ff o wird getrennt - Magnetschalter 25 wird stromlos und fällt ab und trennt durch Unterbrechung des Kontaktes 2 31/32 auch weiter die Stromzufuhr ab. Nachdem Zug auf Signal U ausgefahren ist wird Anfangsfeld U geblockt. Stromschluss: von D > J.W. über 1) A O Kontakt am Anfangsfeld (umgeschaltet)

4) Kontakt am Endfeld E- (Grundstellung)

5) Feldspulen Endfeld Ú W

6) Kontakt am Endfeld - Grundstellung)

7) Kontakt 51/52 ₹4 (Grundstellung) zu eigener Blockstelle I

8) Kontakt 31/32 # 4 (Grundstellung)

9) Kontakt am Anfangsfeld U (umgeschaltet) zum J.W. - zurück

Die Rückblockung:

Von J.W. > Blockstelle II tiber

1) Kontakt am Endfeld W E-O- (umgeschaltet)

2) Signalflügelkontakt (Grundstellung)

3) Kontakt am Endfeld W E O (umgeschaltet)

4) Feldspulen Endfeld W

5) Kontakt 61/62 #4(Grundstellung) zur Blockstelle I

6) Kontakt am Anfangsfeld U H→ (Grundstellung)

7) Feldspulen Anfangsfeld U

8) Kontakt am Anfangsfeld U H-O- (Grundstellung)

9) Kontakt 31/32 € | zur Blockstelle II lo) Kontakt 51/52 € |

11) Kontakt am EndfeldW E-O-(umgeschaltet) zum J. W. ____ zurück, Nach der Ausfahrt U hat die Fahrstrassenfestlegung ausgelöst -Kontakt Ff o ist wieder geschlossen, das Anfangsfeld U wurde geblockt und damit Druck- und Riegelstangen-Kontakt im Stromkreis des Magnetschalter # 2 wieder geschlossen. - Magnetschalter 2 ist angezogen und nach Entblockung des Anfangsfeldes U die Grundstellun wieder hergestellt.

<u>Abgabe der Erlaubnis von I nach II:</u> (vom Anfangsfeld U nach Anfangsfeld x) Beim Drücken des Anfangsfeldes U wird der frühschliessende Kontakt Anfangsfeld U passender Kontakt Approved For Release 2002/01/18 CIA-RDP83-00415R009200060008-5 U.S. OFFICIALS ONLY

Magnetschalters 🔁 l geschlossen - Magnetschalter 🎛 l zieht an. Dadurch sind beim Blocken des Anfangsfeldes U (Erlaubnisabgabe) die 4 Kontakte des Magnetschalters & 1 im Blockstromkreis (Blockstelle I) umgeschaltet.

Stromschluss:

Von J.W. - Blockstelle I 1) Kontakt am Anfangsfeld U H-O (umgeschaltet)

2) Feldspulen Anfangsfeld U

3) Kontakt 21/22 1 (Umgeschaltet) 4) Anschluss 51 1 (51/52 unterbrochen) zur Blockstelle II

5) Kontakt am Anfangsfeld X H-O- (Grundstellung)

6) Feldspulen Anfangsfeld X 7 (Grundstellung)

8) Kontakt 11/12 至 1 (Grundstellung) z 9) Anschluss 61 至 1 (61/62 unterbrochen) 10) Kontakt 41/42 至 1 (umgeschaltet) (Grundstellung) zur Blockstelle I

11) Kontakt am Anfangsfeld U 9-0-(umgeschaltet) zum J.W. > d zurück Jetzt ist Signal U in der Grundstellung durch den geblockten Signalverschluss festgelegt und Signal X durch Entblocken des Anfangsfeldes X (Erlaubnisfeld) frei.

Im Stromkreis des Magnetschalters 2 2 Blockstelle I ist der Riegelstangenkontakt des Anfangsfeldes o umgeschaltet = n - Walso geschlossen, der im Stromkreis des Magnetschalters # 2 Blockstelle bisher geschlosseneg-o- W Kontakt des Anfangsfeldes X ist jetzt getrennt_f-o-

Bezeichnungs-Erläuterungen:

- J.W. = Induktor-Wechselstrom
- J.W. > Stromausgang
- J.W. Stromrückkehr.

SECRET CONTROL U.S. OFFICIALS ONLY